

DVB ASI TS INPUT BOARD



DVB ASI TS input board is designed to convert the ASI TS into parallel DVB TS and can be used with other our boards for building ASI-IP converters modulators and other digital broadcasting equipment.

ASI TS received by DVB ASI TS input board is used for our boards which create streams for further broadcasting in RF or IP. It can be ASI-to-IP converters and [DVB-S-S2-T modulators](#).

Parameters	
Input	
Type of input signal	DVB ASI, electric
Modes of operation	burst, byte
Number of bytes in the packet	188/204
Determining the type of input stream	automatic
Number of inputs	1
Input connector type	BNC
Input voltage	200..880 mV
Input impedance	75 Ohm
Input bitrate	up to 180 Mbps

Output	
Output transport stream bitrate	up to 150 Mbps
Operating mode	byte
Number of bytes in the packet	188
Other	
Indication	LED: carrier lock, frame lock, frame size, error, power
Power supply	+5 VDC +/-5%
Consumed power, no more than	2 W
Module board dimensions	101x61 mm

Taking into consideration that we (UMT LLC) are developer and system integrator, also do not stop on our technical growth and improvement, know that view of all our devices and equipment including their technical parameters may be different from pictures presented on website and parameters listed on each device webpage.

Note! All details customer has to confirm in advance during ordering and before payment. Those parameters that were not specified and / or were not agreed while ordering will be implemented as basic at the discretion of the manufacturer. Each our customer has 1.5 year warranty and 7 year aftersales support for whole range of our products.