

BUC-C40



BUC-C40 is block up-converter with fixed output power P1dB 40 W. BUC-C40 has LED status indication at the rear side.

The 40W C-band BUC is a rugged, compact solid state amplifier (SSPA) with integrated block up converter (BUC) suitable for fixed and mobile satellite communications with high data rate or multicarrier requirements. The 40W C-band BUC is an outdoor, environmentally sealed product that can be mounted close to the antenna feed to reduce waveguide loss.

KEY FEATURES:

- Outdoor SSPA with integrated BUC
- Compact, Lightweight Package
- M&C capability via RS232, Ethernet
- High linearity

Input parameters:	
Input Frequency range	950 – 1525 MHz
Input impedance	50 Ohm
Input VSWR, max	1.5
Input interface	N-type Female
Local Oscillator:	

LO frequency	4900 MHz	
LO Phase noise	@1 kHz	-85 dBc/Hz
	@10 kHz	-95 dBc/Hz
	@100 kHz	-105 dBc/Hz
Output parameters:		
Output frequency range	5850 – 6425 MHz	
Output Power @P1dB, min (GaAs)	40 W (46 dBm)	
Gain, min	66 dB	
IMD3 (two tones)	-25 dBc max 2 signal 5 MHz apart at @P1dB	
Output interface	WR137-G (Waveguide Flange)	
Output VSWR, max	2.0:1	
Frequency Response:		
Flatness over Full Band	± 2 dB (4 dB p-p max)	
Gain flatness 40 MHz	± 0.5 dB	
External frequency	10 MHz	
Power range ref.	-5 dBm to +5 dBm	
Spurious:		
In-band @P1dB, max	-50 dBc	
Out-Band, max	-60 dBc	
LO leakage	-40 dBm	
Image rejection, min	60 dB	

Power Supply:

Input voltage	90-240 VAC, 47-63Hz
Power consumption, max	< 230 W

Environmental:

Operating temperature	-20 to +50
Operating humidity	0 – 95 %

Interfaces:

IF input connector: N-type female; RF output connector: WR137-G
AC connector: PQ14-3; Monitor & Control connector: FQ24-19
Monitor & Control: Serial RS-232, Step Attenuator, Ethernet
LED indicator: Green – OK, Red – Alarm, blink Yellow – MUTE

Mechanical

Dimensions	260x135x92 mm
Weight, max	4.7 kg

Taking into consideration that we (UMT LLC) are developer and system integrator, also do not stop on our technical growth and improvement, know that view of all our devices and equipment including their technical parameters may be different from pictures presented on website and parameters listed on each device webpage.

Note! *All details customer has to confirm in advance during ordering and before payment. Those parameters that were not specified and / or were not agreed while ordering will be implemented as basic at the discretion of the manufacturer. Each our customer has 1.5 year warranty and 7 year aftersales support for whole range of our products.*