DVB ASI TS OUTPUT BOARD



DVB ASI TS output board is designed to convert the parallel DVB TS into ASI TS and can be used with other our boards for building IP-ASI converters, receivers and other digital broadcasting equipment.

ASI TS received by DVB ASI TS output board is used for our boards which create streams for further broadcasting in RF or IP. It can be ASI-to-IP converters and DVB-S-S2-T modulators.

Parameters	
Input	
Output transport stream bitrate	up to 150 Mbps
Operating mode	burst, byte
Output	
Type of signal	DVB ASI, electric
Modes of operation	burst, byte
Number of bytes in the packet	188/204
Determining the type of input stream	automatic
Number of outputs	2 (loop)
Output connector type	BNC

Output voltage	880 mV
Output impedance	75 Ohm
Input bitrate	up to 180 Mbps
Other	
Voltage supply	+5 VDC +/-5%
Power consuption, no more than	2 W
Module board dimensions	112x50 mm

Taking into consideration that we (UMT LLC) are developer and system integrator, also do not stop on our technical growth and improvement, know that view of all our devices and equipment including their technical parameters may be different from pictures presented on website and parameters listed on each device webpage.

Note! All details customer has to confirm in advance during ordering and before payment. Those parameters that were not specified and / or were not agreed while ordering will be implemented as basic at the discretion of the manufacturer. Each our customer has 1.5 year warranty and 7 year aftersales support for whole range of our products.